

Cole-Parmer®

Cole-Parmer® Block Heater, 3 Block, Digital, BH-200D-3 & BH-200D-3-HT

- Choice of 130°C or 200°C maximum temperature
- Three block capacity
- Digital setting and display
- Uniform and stable temperatures



Cole-Parmer® Block Heater, 3 Block, Digital, BH-200D-3 & BH-200D-3-HT



The same precise heating and control of the two block models but with 50% more capacity of a third block. Excellent temperature stability and uniformity is maintained via sensitive electronic controls.

All Cole-Parmer® three block heaters are compatible with the Cole-Parmer® Sample concentrator, for faster sample concentration.

Technical Specification

Specification	BH-200D-3	BH-200D-3-HT
Number of blocks	3	3
Temperature range	Ambient +8°C to 130°C	Ambient +8°C to 200°C
Temperature stability at 37°C	±0.1°C	±0.1°C
Uniformity within block at 37°C	±0.1°C	±0.1°C
Uniformity within block at 130°C	±1°C	±1°C
Display resolution	0.1°C	0.1°C
Dimensions, mm (w x d x h)	310 x 280 x 115	310 x 280 x 115
Net weight, kg (without blocks)	3.2	3.2
Heater power	450W	450W
Electrical supply	230V, 50Hz	230V, 50Hz
IP Rating	31	31

Ordering Information

Description	Ordering Number	Series No.	Model No.	Legacy Sku.
Block heater, 3 block, digital, 130°C	36610-13	BH-200	BH-200D-3	SBH130D/3
Block heater, 3 block, digital, 200°C	36610-23	BH-200	BH-200D-3-HT	SBH200D/3
Block heater, 3 blocks, digital, 130°C, 120V	36610-12	BH-200	BH-200D-3-120	SBH130D/3/120V
Block heater, 3 blocks, digital, 200°C, 120V	36610-22	BH-200	BH-200D-3-HT-120	SBH200D3/120V60



WolfLabs

Pricing on any accessories shown can be found by keying the part number into the search box on our website.

The specifications listed in this brochure are subject to change by the manufacturer and therefore cannot be guaranteed to be correct. If there are aspects of the specification that must be guaranteed, please provide these to our sales team so that details can be confirmed.

www.wolflabs.co.uk

Tel : 01759 301142

Fax : 01759 301143

sales@wolflabs.co.uk

Please contact us if this literature doesn't answer all your questions.