

Microplate Shaker TiMix 5 control



Description

The Microplate Shaker TiMix 5 control guarantees optimal mixing of small sample volumes in microplates, deepweel-plates or other plates in microplate format. The wide choice of different rack systems allows fastening between 8 and 48 microplates. The shaker also has a digital display and programmable control.

Basic Equipment

Basic device without shaking plate, **without rack system**With digital display and programmable control

Loading Capacity

Standard rack system 0052 101 8 microplates
Rack system with pins 0052 096 8 microplates
Standard rack system 0052 101 +
Additional tray 0052 102 16 microplates
RS high clamping pins 0052 104 24 microplates
RS metal clamping pins 0052 125 48 microplates

Option:

Details

Motion: exact orbital motion

Shaking platform: 400 x 300 mm for 8 microplates

Max. load: 5 kg

Shaking speed: 100 - 1400 rpm, in steps of 5

Stroke: 3 mm (Special stroke on request)

Runtime: programmable / continuous

Order No.: 6167 000

Accessory: Standard Rack System TiMix 5

Additional tray TiMix 5

Rack System with clamping pins
Rack System with high clamping pins
Rack System with metal clamping pins

Rack System Combifix KS

Universal tray KS

Incubator Hood TH 15

Technical specifications

Electrical supply: 230 V or 115 V, 50 / 60 H please indicate in case of order

Enclosure protection: IP 21

Heat emission: approx. 25 W **Ambient temperature:** 5°C to 50°C

Relative humidity: $\sim 85\%$

Dimensions (w x d x h): 510 x 490 x 150 mm

Weight: 20 kg



Pricing on any accessories shown can be found by keying the part number into the search box on our website.

The specifications listed in this brochure are subject to change by the manufacturer and therefore cannot be guaranteed to be correct. If there are aspects of the specification that must be guaranteed, please provide these to our sales team so that details can be confirmed.

www.wolflabs.co.uk

Tel: 01759 301142

Fax: 01759 301143

sales@wolflabs.co.uk

Please contact us if this literature doesn't answer all your questions.